

OPEN GENSETS WITH IVECO ENGINE



1500 RPM	400/230 V 50 Hz	Type AI-075	75/60 Kva/KW (PRP)	82/65.6 Kva/KW (LTP)
-----------------	------------------------	--------------------	---------------------------	-----------------------------

Engine: NEF 45SM2
Alternator: ECP 34 -1S/4

Scope of Supply:

The engine and the alternator are mounted together forming a rigid monoblock, the shafts are connected by a flexible disc connection. The monoblock is mounted on a steel base frame via silent blocks. The base frame is including a fuel tank. Starting is electric and it includes a battery. The genset monitoring system consist of a control module.

GEN SET POWER

Voltage	Hz	Phase	Cos Ø	PRP* Kva/KW	LTP** Kva/KW	Amp.
415/240	50	3	0,8	75/60	82/65,6	114,2
400/230	50	3	0,8	75/60	82/65,6	118,5
380/220	50	3	0,8	75/60	82/65,6	124,7
240/120	50	3	0,8	75/60	82/65,6	197,5
230/115	50	3	0,8	75/60	82/65,6	206,1
220/110	50	3	0,8	75/60	82/65,6	215,4

PRP* Kva/KW:

Available electrical power (at a variable load) with a medium of 80% of the indicated maximum power. A 10% overload capability is available

LTP** Kva/KW:

Available electrical power (at a variable load) with a medium fo 80% Available electrical load (at a variable load) during a maximum of 500 hours per year. No overload capability is available.of the indicated maximum power. A 10% overload capability is available


Control Cubicle Alternatives

Manual/Remote Control Cubicle:: STANDARD MCP SAM 712 / OPTIONAL MCP DSE 710
 Automatic Control Cubicle: STANDARD ACP DSE 720 / OPTIONAL ACP DSE 5320

Options::

Please see the price list

TECHNICAL DATA

Engine		Alternator		
Engine type:	NEF 45SM2	Alternator Type:	ECP 34-1S/4	
Eng. Power kW COP:	-	Nº of poles:	4	
Eng. Power kW PRP:	66	Eff. At 3/4 %:	91.9	
Eng. Power kW LTP:	73	Eff. At 4/4 %:	91.5	
Nº Cylinders:	4	Alt. rating PRP kVA III Kw II:	85	
Displacement cm3:	4500	Alt. rating LTP kVA III kW II:	93.5	
Bore/stroke (mm/mm):	104 X 132	Output Power PRP kVA III kW II:	75.5	
Compression ratio:	17,5	Output Power LTP kVA III kW II:	83.5	
Cooling:	WATER	Current Amp PRP:	108.4	
Injection:	DIRECT	Current Amp LTP:	119.9	
Aspiration:	TURBO	Standard Circuit Breaker (Amp):	125 IV	
Standard governor:	MECHANICAL	Xd (%):	325	
Governing control quality:	G2	X'd (%):	22.3	
Speed droop mech gov. (%):	4	X:	7.4	
Exhaust gases temperature (°C):	525	Nº of wires:	12	
Exhaust gases flow (m3/h):	900	Insulation:	H	
Max Exh. Back pres. (mbar):	60	Regulator AVR:	UVR6	
Coolant capacity (lit.):	18.5	Protection:	IP21	
Cooling air flow (m3/h):	10295	DIMENSIONS		
Max allow. Intake dep. (mbar):	50	Height:	1570 mm	
Combustion air flow (m3/h):	426	Width:	1030 mm	
Oil cap. (Litres):	12.8	Length:	1880 mm	
Oil cons. (kg/hr or % of fuel cons):	0.10%		Weight:	1080 kgs
Min oil press warning (bar):	2		Tank:	198 lit
Fuel cons. 25% lit/h:	4.3			
Fuel cons. 50% lit/h:	8.6			
Fuel cons. 75% lit/h:	12.7			
Fuel cons. 100% lit/h:	17.1			
Electric system VDC:	12V			
Type:	Neg to ground.			
Battery (Ah):	96			
Starting motor (kW):	3			
Flywheel Housing:	SAE3/11			

Technical information available in download section.:

Engine technical data	Alternator Technical data	Gen Set Drawing	Instalation drawing	Control cubicle descr.
Engine manual	Alternator Manual	Gen Set Manual	Gen Set Condensed Man.	Controler manual

Control Cubicles



MANUAL -REMOTE START CONTROL MODULE: MCP SAM 712

SAM 712 CONTROLLER

- Manual or Automatic remote start controller, Selector switch for Off, Man and Auto with key. Complete engine protection functions with alarms visualised via LEDs in the front. The controller is set up via 6 DIP switches in the rear of the case.
- Standard circuit breaker.and diferencial relay.



MANUAL-REMOTE START : MCP DSE 710

DSE 710 CONTROLLER

- The Model 710 is a Manual or Automatic Start Control Module.
- The module is used to manually or automatically start and monitor a generator set.
- The module also provides indication of operational status and fault conditions,
 - Control via interface or cable via PC
- Operation of the module is via pushbutton controls mounted on the front panel with STOP/RESET, MANUAL, AUTO and START pushbuttons.
- Standard Circuit Breaker and differential relay.



AUTOMATIC CONTROL MODULE : ACP DSE 720

DSE 720 CONTROLLER

- The Model 720 is a Manual or Automatic Start Control Module. The module is used to manually or automatically start and monitor a generator set.
- Operation of the module is via pushbutton controls with STOP/RESET, MANUAL, TEST, AUTO and START
- Communication via interface or cable via PC.Selected timers and alarms can be altered by the customer from the front panel. Alterations to the system are made using the 810 interface and a PC. This interface also provides real time diagnostic facilities. It is also possible to monitor and control the system via PC up to 100metres (111 yards) from the controller.
- Standard IV poles circuit breaker (until 85 Kva).



AUTOMATIC/MANUAL CONTROL MODULE: ACP-MCP DSE 5320

DSE 5320 CONTROLLER

- The Model 5320 is an Automatic Mains Failure Control Module. The module is used to monitor a mains supply and automatically start a standby generator set..
- Operation of the module is via pushbutton controls with STOP/RESET, MANUAL, TEST, AUTO and START
- The controller has a J 1939 CANBus interface for connection to modern engine ECU's. This enables engine protection and instrumentation without requiring additional sensors. Engine diagnostic information removes the need for both service equipment and cryptic diagnostic
- Comprehensive remote communication via RS232 port connecting via modem or PC.It is also possible to monitor and control the system via PC up to 100metres (111 yards) from the controller
- Standard IV poles circuit breaker (until 85 Kva.)